# **Yealink IP Phone Quick Call Guide**

#### Call - Handset

**Dial** the 10-digit phone number, Press **Send** soft key (or # or OK)

#### OR:

**Dial** 10-digit number, **Pick up** the handset

### **Call - Speakerphone**

Press **Speaker** button **Dial** 10-digit phone number

Press **Send** soft key (or # or OK)

### OR:

**Dial** 10-digit number Press **Speaker** button

### **Transfer (Announce caller)**

Press **TRAN** button (or Transfer soft key) **Dial** 3 digit extension number (or 10-digit #)

#### OK

Wait for party to answer Announce the call Hang up

*Note*: For a denied call, press the flashing line button where the call came in on (twice if multiple calls are happening) to get the caller back

# **Transfer (Blind)**

Press **TRAN** button (or Transfer soft key) **Extension** number (or 10-digit #) **OK** [will pass through ID of caller]

# **Transfer directly to Voice Mail**

Press **TRAN** (or Transfer soft key) **Extension** number

\* button

**TRAN** (or Transfer soft key)

OK

### Intercom (hands-free)

Press ICOM

then **Extension button** or three digit # **Ok** or Send

**Park** (park & announce park # to recipient for them to pick up)

### **EITHER:**

Press the Park button where you want to place the call, Park 1, Park 2, etc. Your call will be transferred to that park postion.

#### OR:

**TRAN** button (or Transfer soft key) \***70** 

ОК

System will issue park number to announce

### Park Pick Up

Press the illuminated Park 1, 2, or 3 etc.

#### OR:

Dial \*71, Park position number, 1, 2, etc OK

So \*711 would answer Park 1, \*712 answer Park 2. etc.

# **Conference Calling**

While on first call, press **Conference soft key** 

**Dial** second call

When answered, press **Conference** soft

# Page All Phones

Press the **Left Arrow key** on the directional pad
Press **OK** button

Make your announcement